



iJRASET

International Journal For Research in
Applied Science and Engineering Technology



INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 4

Issue: V

Month of publication: May 2016

DOI:

www.ijraset.com

Call: ☎ 08813907089

E-mail ID: ijraset@gmail.com

Soft-Switching Design of Isolated Boost Converter with Coupled Inductor

R.Vignesh¹, P. Madhavaraj², S.Gomathi³

^{1,2}UG Student, ³Assistant Professor, Electrical and Electronics Engineering
St.Joseph's Institute Of Technology, Chennai, Tamilnadu, India

Abstract— In this paper the soft-switching design of isolated boost converter is analysed. the participation of resonance in the voltage doubler circuit, clamping capacitor and the reactance leakage in the coupled inductor. By choosing the proper magnetic inductance of the coupled inductors, soft-switching design (i.e) zero voltage switching is achieved to on the MOSFET without any use of additional devices. The Duty cycle range is adjusted to achieve Zero voltage switching and the optimal operation point is achieved with the reduced current ripples, when duty cycle reaches 0.5.

Index Terms—About four key words or phrases in alphabetical order, separated by com

I. INTRODUCTION

In present Sineario, high voltage gain dc–dc boost converters play more and more imp role in many industry applications such as uninterrupted power supplies, electric traction, distributed photovoltaic (PV) generation systems, fuel cell energy conversion systems, automobile HID headlamps, and some medical equipments. THE conventional single-switch boost converter is widely employed in the distributed front-end power factor correction applications, such as the server power systems due to its advantages of simple structure, low cost, and easy implementation. At ideal continuous current mode (CCM) operation, the voltage gain of the conventional boost converter is only determined by the switch duty cycle, which means only one control freedom is available to regulate the output voltage. Therefore, its optimal voltage conversion ratio limited is to a p p r o x i m a t e l y f o u r t i m e s w i t h a r e l a t i v e l y h i g h efficiency. However, nearly or even over 10 times of voltage gain is expected in some high step-up applications. For example, the automobile high-intensity-discharge headlamps usually need to convert 12V onboard battery up to 100V at steady operation, even to 400V during the start-up stage. The 48V standard battery is required to be boosted to nearly 400V for back-up uninterruptable power systems. Furthermore, the output voltage of the individual photovoltaic (PV) cell is generally lower than 60V. However, the grid-connected ac voltage is 220V for single-phase local utility in most countries, which also calls for high step-up and high-efficiency converters to realize the integrated PV modules. In these high step-up and high output voltage applications, the extremely large duty cycle is inevitable with the conventional boost converter, which increases the switch peak current, deteriorates the switching condition, and expands the conduction and switching losses. In these high step-up and high output voltage applications, the extremely large duty cycle is inevitable with the conventional boost converter, which increases the switch peak current, deteriorates the switching condition, and expands the conduction and switching losses. Furthermore, from the small-signal model analysis, once the duty cycle is close to 1, the dynamic response of the boost converters is limited because there is only a small duty cycle regulation range during the transient operation. How to realize high step-up dc/dc converters without extreme duty cycle to improve the system performance is becoming one of the most emergent technologies for power electronics researchers.


A **push–pull converter** is a type of DC-to-DC converter, a switching converter that uses a transformer to change the voltage of a DC power supply. The distinguishing feature of a push-pull converter is that the transformer primary is supplied with current from the input line by pairs of transistors in a symmetrical push-pull circuit. The transistors are alternately switched on and off, periodically reversing the current in the transformer. Therefore current is drawn from the line during both halves of the switching cycle. This contrasts with buck-boost converters, in which the input current is supplied by a single transistor which is switched on and off, so current is only drawn from the line during half the switching cycle. During the other half the output power is supplied by energy stored in inductors or capacitors in the power supply.

However, push–pull more commonly refers to a two-switch topology with a split primary winding.

In any case, the output is then rectified and sent to the load. Capacitors are often included at the output to filter the switching noise. In practice, it is necessary to allow a small interval between powering the transformer one way and powering it the other: the

“switches” are usually pairs of transistors (or similar devices), and were the two transistors in the pair to switch simultaneously there would be a risk of shorting out the power supply. Hence, a small wait is needed to avoid this problem. This wait time is called "Dead Time" and is necessary to avoid transistor shoot-through.

drawbacks of push-pull converter:High input current ripple because the current in the primary side is discontinuous, large transformer volume,leakage inductance which degrades power density,leakage inductance which degrades circuit performance.Reverse-recovery problem of secondary diodes is still remained and duty ratio must be larger than 0.5 to achieve ZVS on of the main MOSFETs.In this paper the soft-switching design of isolated boost converter is analysed,resonance analysis and soft-switching design of the isolated boost converter with coupled inductors are presented. Compared with the former proposed converter, both ZVS on of the main MOSFETs and zero-current switching (ZCS) off of the secondary diodes are obtained collectively at the same working conditions without any additional devices. Moreover, the range of duty ratio is enlarged due to the design and an optimal operation point is obtained when duty ratio approaches 0.5 and the ripple of input current moves in close to zero. The volume of the converter can also be decreased because of



International Journal for Research in Applied Science & Engineering Technology (IJRASET)

smaller transformers and smaller capacitors. A dc/dc converter for vehicle inverter is implemented to verify the design. Be sure that the symbols in your equation have been

Design of the Optimized Resonance

In this particular vehicle inverter application, operation point at $D = 0.5$ is preferred because of minimized input current ripple. ZVS on of main switches can be achieved when magnetizing inductances are small enough. Meanwhile, ZCS off of secondary diodes is designed within the whole input voltage and load range. Due to relatively high turn ratio of transformer, C_c needs to be extraordinarily large to obtain secondary-dominant resonance. In the designed converter, a communal clamping capacitor C_c is used and its capacitance is properly not large due to the design of optimized resonance. Thus, the designed resonance is between the aforementioned two resonances and the volume of capacitor is reduced. Three factors should be considered for design of this optimized resonance.

Duration of resonance. In order to achieve ZCS off of secondary diodes, duration of resonance should be shorter than minimal overlapping interval ($D > 0.5$) or nonoverlapping interval ($D < 0.5$). However when duration of resonance is shortened, the peak of resonant current rises to transfer equivalent energy. That means C_c and C_r should be sufficiently large to alleviate current stress of both primary and secondary side.

Ripple of clamping voltage. Main MOSFETs will sustain high voltage stress if C_c is too small. Hence, C_c should restrict the ripple of clamping voltage into an acceptable range.

Capacitor volume. After taking the previous two into consideration, a combination of C_c and C_r should be adopted to get minimal volume of capacitors.

In this converter, C_r is 47 nF and C_c is 3 μ F while turn ratio of transformer is 3:3:24. Obviously, the resonance is the one between primary-dominant resonance and secondary-dominant resonance.

Mode of operation -Operational Principle for $D < 0.5$

When D is small than 0.5, resonance operates at non-overlapping interval

Mode 1 [t_0, t_1]

S_1 is turned OFF at t_0 while S_2 is off, Inductor L_{p1} and L_{p2} are discharging and di/dt equals $(U_{in} - U_{Cc}) / L_p$. Due to small inductance of L_{p1} and L_{p2} , i_{Lp2} is under zero at t_1 ,

The reverse current is flowing from clamping capacitor C_c , auxiliary MOSFET S_4 to inductor L_{p2} , No energy is transferred to secondary side.

Mode 2 [t_1, t_2]

S_4 is turned OFF at t_1 when i_{Lp2} is reverse, Inductor L_{p2} discharges parasitic capacitor C_{p2} of S_2 for free-wheeling, If the reverse current of L_{p2} is large enough, there will be sufficient energy to discharge u_{DS2} to zero at t_2 .

Mode 3 [t_2, t_3]

S_2 is turned ON at t_2 when u_{DS2} reaches zero. ZVS on of S_2 is achieved. S_1 is still off. Hence, inductor L_{p1} is discharging and di/dt equals $(U_{in} - U_{Cc}) / L_p$, Inductor L_{p2} is charging and di/dt equals U_{in} / L_p . Secondary circuit begins to conduct. Transformer T_1 works as a flyback converter and transformer T_2 works as a forward converter, Leakage inductor of transformer, clamping capacitor C_c and voltage doubler capacitor C_r start to resonate, Therefore, both i_{Lp1} and i_{Lp2} contain magnetizing current and resonant current.

Mode 4 [t_3, t_4]

Secondary current i_L s decreases to zero at t_3 and resonant circuit is cut off by diode Do_2 , Therefore, secondary diode is turned OFF softly and reverse recovery problem is removed, Inductor L_{p1} is still discharging with rate determined by $(U_{in} - U_{Cc}) / L_p$, Inductor L_{p2} is still charging with rate determined by U_{in} / L_p .


International Journal for Research in Applied Science & Engineering Technology (IJRASET)

II. SIMULATION OUTPUT RESULT


International Journal for Research in Applied Science & Engineering Technology (IJRASET)

!2


INPUT VOLTAGE:




INPUT POWER:




Output voltage




Gate Pulse with Drain source voltage of all Switch




Output current




Gate Pulse with Drain source voltage of S1




Output power



Primary Current



Output voltage



Simulation Experimental Result

The above fig shows the Comparison of Gate Pulse with Drain source voltage of S

International Journal for Research in Applied Science & Engineering Technology (IJRASET)

IV. CONCLUSION

In this project, resonance analysis and soft-switching design of an isolated boost converter with coupled inductors are presented. The choosing appropriate magnetic inductance of the coupled inductors, ZVS on of the main MOSFETs and ZCS off of the secondary diodes can be achieved collectively at the same working conditions without any additional devices. At last, a 150 W, 12–360 V high efficiency prototype converter is built to verify the analysis, and the experimental results illustrate that the proposed converter is a competitive candidate for low power and high step-up applications with isolation requirements.

V. ACKNOWLEDGMENT

The preferred spelling of the word “acknowledgment” in American English is without an “e” after the “g.” Use the singular heading even if you have many acknowledgments. Avoid expressions such as “One of us (S.B.A.) would like to thank” Instead, write “F. A. Author thanks” **Sponsor and financial support acknowledgments are placed in the unnumbered footnote on the first page.**

REFERENCES

- [1] S.-J. Jang, C.-Y. Won, B.-K. Lee, and J. Hur, “Fuel cell generation system with a new active clamping current-fed half-bridge converter,” *IEEE Trans. Energy Convers.*, vol. 22, no. 2, pp. 332–340, Jun. 2007.
- [2] Z. Zhang, Z. Ouyang, O. C. Thomsen, and M. A. E. Andersen, “Analysis and design of a bidirectional isolated DC–DC converter for fuel cells and supercapacitors hybrid system,” *IEEE Trans. Power Electron.*, vol. 27, no. 2, pp. 848–859, Feb. 2012.
- [3] O. Hegazy, J. Van Mierlo, and P. Lataire, “Analysis, modeling, and implementation of a multidevice interleaved DC/DC converter for fuel cell hybrid electric vehicles,” *IEEE Trans. Power Electron.*, vol. 27, no. 11, pp. 4445–4458, Nov. 2012.
- [4] L. Tang and G.-J. Su, “An interleaved reduced-component-count multivoltage bus dc/dc converter for fuel cell powered electric vehicle applications,” *IEEE Trans. Power Electron.*, vol. 44, no. 5, pp. 1638–1644, Sep./Oct. 2008.
- [5] Y. Park, B. Jung, and S. Choi, “Nonisolated ZVZCS resonant PWM DC–DC converter for high step-up and high-power applications,” *IEEE Trans. Power Electron.*, vol. 27, no. 8, pp. 3568–3575, Aug. 2012.
- [6] I. Aharon and A. Kuperman, “Topological overview of powertrains for battery-powered vehicles with range extenders,” *IEEE Trans. Power Electron.*, vol. 26, no. 3, pp. 868–876, Mar. 2011.
- [7] R. L. Andersen and I. Barbi, “A ZVS-PWM three-phase current-fed push–pull DC–DC converter,” *IEEE Trans. Ind. Electron.*, vol. 60, no. 3, pp. 838–847, Mar. 2013.
- [8] H. Ma, L. Chen, and Z. Bai, “An active-clamping current-fed push-pull converter for vehicle inverter application and resonance analysis,” in *Proc IEEE Int. Symp. Ind. Electron.*, 2012, pp. 160–165.
- [9] Y. Wang, Q. Liu, J. Ma, and H. Ma, “A new ZVCS resonant voltage-fed push-pull converter for vehicle inverter application,” in *Proc IEEE Int. Symp. Ind. Electron.*, 2013, pp. 1–6.
- [10] V. Vaisanen, T. Riipinen, J. Hiltunen, and P. Silventoinen, “Design of 10 kW resonant push-pull DC–DC converter for solid oxide fuel cell applications,” in *Proc. IEEE 14th Eur. Power Electron. Appl.*, 2011, pp. 1–10.
- [11] T.-F. Wu, J.-C. Hung, J.-T. Tsai, C.-T. Tsai, and Y.-M. Chen, “An activeclamp push–pull converter for battery sourcing applications,” *IEEE Trans. Ind. Appl.*, vol. 44, no. 1, pp. 196–204, Jan./Feb. 2008.
- [12] E.-H. Kim and B.-H. Kwon, “High step-up resonant push-pull converter with high efficiency,” *IET Trans. Power Electron.*, vol. 2, no. 1, pp. 79–89, Jan. 2009.
- [13] I. Boonyaroonate and S. Mori, “A new ZVCS resonant push–pull DC/DC converter topology,” in *Proc. IEEE 17th Annu. Appl. Power Electron. Conf.*, 2002, vol. 2, pp. 1097–1100.
- [14] Y. Zhao, W. Li, Y. Deng, and X. He, “Analysis, design, and experimentation of an isolated ZVT boost converter with coupled inductors,” *IEEE Trans. Power Electron.*, vol. 26, no. 2, pp. 541–550, Feb. 2011.
- [15] S.-K. Han, H.-K. Yoon, G.-W. Moon, M.-J. Youn, Y.-H. Kim, and K.-H. Lee, “A new active clamping zero-voltage switching PWM current-fed half bridge converter,” *IEEE Trans. Power Electron.*, vol. 20, no. 6, pp. 1271–1279, Nov. 2005.
- [16] C.-L. Chu and C.-H. Li, “Analysis and design of a current-fed zero-voltage-switching and zero-current-switching CL-resonant push-pull dc–dc converter,” *IET Trans. Power Electron.*, vol. 2, no. 4, pp. 456–465, Jul. 2009.
- [17] J.-M. Kwon, K. Eung-Ho, B.-H. Kwon, and K.-H. Nam, “High-efficiency fuel cell power conditioning system with input current ripple reduction,” *IEEE Trans. Ind. Electron.*, vol. 56, no. 3, pp. 826–834, Mar. 2009.
- [18] W. Li, L. Fan, Y. Zhao, X. He, D. Xu, and B. Wu, “High-step-up and high-efficiency fuel-cell power-generation system with active-clamp flyback–forward converter,” *IEEE Trans. Ind. Electron.*, vol. 59, no. 1, pp. 599–610, Jan. 2012.



10.22214/IJRASET



45.98



IMPACT FACTOR:
7.129



IMPACT FACTOR:
7.429



INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089  (24*7 Support on Whatsapp)